

### Features

- 3-in-1 stud, metal and AC voltage detector
- Ergonomically designed for comfort and grip
- Bargraph allows for quick and accurate detection
- Easy operation
- Auto power off
- Includes battery

### Specifications

#### Detection Depth

|          |                    |
|----------|--------------------|
| Stud:    | Up to 0.98" (25mm) |
| Metal:   | Up to 2.56" (65mm) |
| Voltage: | Up to 1.96" (50mm) |

#### General Specifications

|                         |                                       |
|-------------------------|---------------------------------------|
| Display:                | LCD Display with bargraph             |
| Auto Power Off:         | Yes (after 20 seconds)                |
| Low Battery Indicator:  | Yes                                   |
| Power Supply:           | 9V Battery                            |
| Product Certifications: | CE                                    |
| Operating Temperature:  | 19.4 to 104°F (-7 to 40°C)            |
| Storage Temperature:    | -4 to 122°F (-20 to 50°C)             |
| Dimensions:             | 6.3 x 3.2 x 1.3"<br>(159 x 82 x 32mm) |
| Weight:                 | 7.2oz (203g)                          |

| Model  | Description                      |
|--------|----------------------------------|
| R9090  | Stud, Metal and Voltage Detector |
| CA-05A | Soft Carrying Case               |

